

EZ TRANSFORMER AND CONTROLLER ENCLOSURE

EZ TRANSFORMER AND CONTROLLER ENCLOSURE

This durable polycarbonate enclosure is designed to keep your electrical components (transformers and controllers) dry and to clean up your installation. The enclosure is built to withstand the elements and is completely watertight.

Product ID: EZENCLOSURE

Dimensions: Width: 10.75" X Length: 13.5" L X Depth: 6.4"



UL-508A/50 Type 3R, 4 4X and 12 Industrial Enclosure File No.: E319779



INSTALLATION INSTRUCTIONS

Mounting System – A mounting system that provides for various mounting options has been provided with the DEKOR® EZ Transformer and Controller Enclosure. To connect the mounting brackets, turn the enclosure so that the backside is visible. Place the mounting brackets over the octagon bosses either horizontally, diagonally, or vertically, and fasten them with ¼"-20 x .025" SS, countersunk phillips drive screws (torque limit = 30 in. lbs.). The enclosure can be mounted vertically (ie. on a wall) or horizontally (ie. table top).

Lid/Door – The lid/doors have a gasket to seal against the base. Secure the lid/door to the base with screws, latches or screws and latches. Make sure the lid/door, gasket, and base are properly aligned. Four #10-32 x 0.75" SS, phillips drive screws have been provided.

Screws: Screw down in four corners with screws provided (torque limit – 15 in. lbs.).

Screws & Latches: Screw down four corners or the two outside corners furthest from the hinge with screws provided (torque limit – 15 in. lbs.). Secure latches to base and close on lid/door.

Latches: Secure latches to base and close on lid/door.

CONSIDERATIONS

- If the enclosure is provided with specified modifications, installed accessories shall be of the same environmental rating.
- Bonding between conduit connections is not automatic and must be provided as a part of the installation. Do not use PVC cement for bonding.
- Conduit holes may be cut using standard hole screws. Secure the conduit, the connector and the locknut thru a pre-drilled hole. For metallic conduit, secure a grounding bushing over the connector locknut. All threaded inserts in the enclosure and for cover attachment are brass #10-32.
- Any fittings used, including conduit fittings and/or bonding between grounding bushings/lugs or between the grounding bushings/lugs and the devices installed inside the enclosure must be according to applicable governing Electrical Code.
- Enclosure drilled for conduit or other modifications voids the warranty and may not be returned.
- Conduit must be aligned into or out of enclosure to prevent enclosure damage due to bending stress in enclosure walls.
- A drainage hole may be created for 3R applications by drilling a 1/8 – ¼ inch hole on the enclosure side facing ground.
- For use in ordinary industrial applications and locations.

Before using the product, the user is advised and cautioned to make their own determination and assessment of the safety and suitability of the product for the specific use in question and is further advised against relying on the information contained herein or previously represented as it may relate to any specific use or application. It is the ultimate responsibility of the user to ensure that the product is suited and the information is applicable to the user's specific application. DEKOR® Lighting does not make, and expressly disclaim, all warranties or merchantability or fitness for a particular purpose, regardless of whether oral or written, express or implied, or allegedly arising from any usage of any trade or from any course of dealing in connection with the use of the information contained herein, previously represented or the product itself. The user expressly assumes all risk and liability, whether based in contract, tort or otherwise, in connection with the use of information contained herein, previously represented or the product itself. Further, information contained herein or previously represented is given without reference to any intellectual property issues, as well as federal, state or local laws which may be encountered in the use thereof. Such questions should be investigated by user.

For questions please contact us at 1-800-258-0344 or customerservice@dekorlighting.com